

# Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240 VAC



U5882-X



U5906-X

## Specifications

- 4 terminals with 5th terminal option.
- Horn bypass option available.
- Available in 60, 100, 150 & 200 amps.
- Optional barrel lock provision.
- Separate lockable breaker reset cover.
- Listed under UL 67 as "suitable only for use as service equipment"—file number E32628.
- 125 amps or 200 amps (per position) continuous duty ringless meter socket. Overall ampere rating limited to main circuit breaker rating.
- For use on 120/240 volt single phase applications.
- Short circuit withstand rating 22K AIC as standard. See wiring diagrams on back page for series rating compatibility.
- Type 3R enclosure constructed with G90 galvanized steel.
- Light gray polyester powder coat finish.
- Service entrance overhead or underground. OH has up to 4" hub opening and UG has up to 4" knockout.
- Wire terminations accept copper or aluminum conductors. Line & neutral: studs Ground: #14-2/0
- Plug-on main circuit breaker: 60 and 100 amp type **Q** small frame, 150 & 200 amp type **QNR** large frame.
- Lockable breaker reset cover.

## 4 Terminals | Multi-Position Meter Main | Ringless

125 Amps/Position Catalog Number	200 Amps/Position Catalog Number	Positions	Service	Connectors CU/AL	Dimensions		
				Line	D"	W"	H"
U5902-X	U5882-X	2	OH/UG	3/8" x 16 Stud	5 1/8"	26 1/2"	30"
U5903-X	U5882-X	3	OH/UG	3/8" x 16 Stud	5 1/8"	34 5/8"	30"
U5904-X	U5882-X	4	OH/UG	3/8" x 16 Stud	5 1/8"	42 5/8"	30"
U5905-X	U5882-X	5	OH/UG	3/8" x 16 Stud	5 1/8"	51 1/20"	30"
U5906-X	U5882-X	6	OH/UG	3/8" x 16 Stud	5 1/8"	59 3/10"	30"

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements before ordering or installing equipment.



# Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240 VAC


## Notes

- **Optional:** Factory installed breakers are available—consult factory.
- **AIC Rating:** All models are rated 22K AIC when used with approved breakers rated at 22K.
- **Hub:** Units supplied with one (1) closing plate. Order hubs separately, see accessories page.
- **Fifth Terminal:** For field installed fifth terminal, order K5T.
- **Connectors:** Socket is supplied with 3/8" - 16 hex head nuts with Belleville washers. For connector lug kits, order as extra from chart on the accessories page. Separate lug kits are required for line and load.

## Breaker Chart - 10K AIC (unless noted 22K)

Manufacturer	Cutler Hammer	Siemens	G.E. (50 Amp Max)	Square D
125 Amps or Less	BR, HQP, QPGF	QP, QPH (22K)	THQL, THQL-GF	Homeline
150-200 Amp	BR, BJ	QN, QNH (22K)	—	—

## Accessories

					
<b>K5T</b> Fifth terminal	<b>112993</b> Meter front	<b>1135467</b> Lower front	<b>1133923</b> Wireway front	<b>QN2200H</b> Circuit breaker	<b>Q2100H</b> Circuit breaker

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements before ordering or installing equipment.

