

Current Transformer Cabinets

Two Rivers Electric Utility Area Units | UL listed

Top Service Entry

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
TRM-403-6	400	600	1Ø3W	65kA	42	20	8
TRM-403-8	400	600	3Ø3W	65kA	42	20	8
TRM-404-13	400	600	3Ø4W	65kA	42	20	8
TRM-603-6	600	600	1Ø3W	65kA	42	24	8
TRM-603-8	600	600	3Ø3W	65kA	42	24	8
TRM-604-13	600	600	3Ø4W	65kA	42	24	8
TRM-803-6	800	600	1Ø3W	65kA	42	24	8
TRM-803-8	800	600	3Ø3W	65kA	42	24	8
TRM-804-13	800	600	3Ø4W	65kA	42	24	8
TRM-1203-8	1200	600	3Ø3W	85kA	48	36	14
TRM-1204-13	1200	600	3Ø4W	85kA	48	36	14
TRM-1603-8	1600	600	3Ø3W	85kA	48	36	14
TRM-1604-13	1600	600	3Ø4W	85kA	48	36	14

Bottom Service Entry

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
TRM-403-6	400	600	1Ø 3W	65kA	42	20	8
TRM-403-8	400	600	3Ø 3W	65kA	42	20	8
TRM-404-13	400	600	3Ø 4W	65kA	42	20	8
TRM-603-6UG	600	600	1Ø 3W	65kA	48	46	12
TRM-603-8UG	600	600	3Ø 3W	65kA	48	46	12
TRM-604-13UG	600	600	3Ø 4W	65kA	48	46	12
TRM-803-6UG	800	600	1Ø 3W	65kA	48	46	12
TRM-803-8UG	800	600	3Ø 3W	65kA	48	46	12
TRM-804-13UG	800	600	3Ø 4W	65kA	48	46	12
TRM-1203-8UG	1200	600	3Ø 3W	85kA	48	46	12
TRM-1204-13UG	1200	600	3Ø 4W	85kA	48	46	12
TRM-1603-8UG	1600	600	3Ø 3W	85kA	48	54	14
TRM-1604-13UG	1600	600	3Ø 4W	85kA	48	54	14
TRM-2004-13UG	2000	600	3Ø 4W	85kA	72	60	20
TRM-3004-13UG	3000	600	3Ø 4W	85kA	72	60	20

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.

