



Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240V | NEC 2020 Compliant



U5882-X



U5906-X

Specifications

- Four terminals with fifth terminal option.
- Horn bypass option available, add -KK to end of part number.
- Available in 60, 100, 150 & 200 Amps.
- Optional barrel lock provision.
- Separate lockable breaker reset cover.
- Listed under UL-67 as "suitable only for use as service equipment"—file number E32628.
- 125 Amps or 200 Amps (per position) continuous duty ringless meter socket. Overall ampere rating limited to main circuit breaker rating.
- For use on 120/240V single phase applications.
- Short circuit withstand rating 22K AIC as standard.
- NEMA 3R enclosure constructed with G90 galvanized steel.
- Light gray polyester powder coat finish.
- Service entrance overhead or underground. OH has up to 4 inch hub opening and UG has up to 4 inch knockout.
- Wire terminations accept copper or aluminum conductors. Line & neutral: Studs, Ground: #14-2/0
- Plug-on main circuit breaker: 60 and 100 Amps type **Q** small frame, 150 & 200 Amps type **QNR** large frame.
- Lockable breaker reset cover.

4 Terminals | Multi-Position Meter Mains | Ringless

125 Amps/Position Catalog Number	200 Amps/Position Catalog Number	Positions	Service	Connectors CU/AL	Dimensions		
				Line	D"	W"	H"
U5902-X	U5882-X	2	OH/UG	3/8" x 16 Studs	5 1/8	26 1/2	30
U5903-X	U5882-X	3	OH/UG	3/8" x 16 Studs	5 1/8	34 5/8	30
U5904-X	U5882-X	4	OH/UG	3/8" x 16 Studs	5 1/8	42 4/5	30
U5905-X	U5882-X	5	OH/UG	3/8" x 16 Studs	5 1/8	51 1/20	30
U5906-X	U5882-X	6	OH/UG	3/8" x 16 Studs	5 1/8	59 3/10	30

Notes

- **Optional:** Factory installed breakers are available—consult factory.
- **AIC Rating:** All models are rated 22K AIC when used with approved breakers rated at 22K.
- **Hub:** Units supplied with one closing plate.
- **Fifth Terminal:** For field-installable fifth terminal, order **K5T**.
- **Connectors:** Socket is supplied with 3/8" - 16 hex head nuts with Belleville washers. Separate lug kits are required for line and load.

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.





Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240V

Breaker Chart - 10K AIC (unless noted 22K)

Manufacturer	Cutler-Hammer	Siemens	GE (50 Amp Max)	Square D
125 Amps or Less	BR, HQP, QPGF	QP, QPH (22K)	THQL, THQL-GF	Homeline
150-200 Amps	—	QN, QNH (22K)	—	—

Accessories

					
K5T Fifth terminal	112993 Meter front	1135467 Lower front	1133923 Wireway front	QN2200H Circuit breaker	Q2100H Circuit breaker

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

