MILBANK ENERGYAT WORK

U5925-O-200




Catalog Number	U5925-O-200
Marketing Product Description	4 Terminal Ringless Plain Top 1-200 Ampere Main Breaker 8 Branch Circuit Single Pedestal Direct Bury
UPC	784572576568
Length (IN)	4.5
Width (IN)	14
Height (IN)	78
Brand Name	Milbank
Туре	Ringless Meter Socket
Application	Meter Socket With Main And Load Center
Standard	UL Listed;Type 3R
Voltage Rating	Up to 240 Volts Alternating Current
Amperage Rating	200 Continuous Ampere
Phase	1 Phase
Frequency Rating	60 Hertz
Size	4.5L x 14W x 78H
Number Of Cutouts	1
Cutout Size	One 200 Ampere Main Breaker
Cable Entry	Underground
Terminal	Lay in

Insulation	Glass Polyester
Mounting	Pedestal
Enclosure	G90 Galvanized Steel with Powder Coat Finish
Jaw Quantity	4 Terminal
Bypass Type	No Bypass
Number of Meter Positions	1 Position
Equipment Ground	Ground Bar
Hub Opening	Plain Top
Line Side Wire Range	6 AWG - 350 kcmil
Load Side Wire Range	6 AWG - 350 kcmil
Number Branch Circuits	8
Number Of Receptacles	0

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

FEATURE TABLE		
ITEM	QTY	DESCRIPTION
А	4	U/L MNTG.EMBOSS
В	1	5/16 SOLID K.O.
С	1	1/4, 1/2 CONC. K.O.
D	1	1/2, 3/4 CONC. K.O.
Е	2	1/2, 3/4, 1 CONC. K.O.
F	3	³ ⁄ ₄ , 1, 1 ¹ ⁄ ₄ , 1 ¹ ⁄ ₂ , 2 CONC. K.O.
G	3	1, 1½, 2, 2½ CONC. K.O.







All dimensions are +/- 1/16". Drawing views are not to scale.

Version:

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electricity and must requirements with a licensed All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.