

Current Transformer Cabinets

City of Norway Area Units | UL listed



NORM-804-13UG

Overhead Entry & Underground Exit or Underground Entry & Overhead Exit

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
NORM-403-6	400	250	1Ø3W	65kA	42	20	8
NORM-403-8	400	250	3Ø3W	65kA	42	20	8
NORM-404-13	400	250	3Ø4W	65kA	42	20	8
NORM-603-6	600	250	1Ø3W	65kA	42	24	8
NORM-603-8	600	250	3Ø3W	65kA	42	24	8
NORM-604-13	600	250	3Ø4W	65kA	42	24	8
NORM-803-6	800	250	1Ø3W	65kA	42	24	8
NORM-803-8	800	250	3Ø3W	65kA	42	24	8
NORM-804-13	800	250	3Ø4W	65kA	42	24	8
NORM-1203-8	1200	250	3Ø3W	85kA	48	36	14
NORM-1204-13	1200	250	3Ø4W	85kA	48	36	14

277/480V Units with provisions for mounting three potential transformers

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
NORM-464-13	400	600	3Ø4W	65kA	48	36	14
NORM-664-13	600	600	3Ø4W	65kA	48	36	14
NORM-864-13	800	600	3Ø4W	65kA	48	36	14
NORM-1264-13	1200	600	3Ø4W	85kA	48	46	12

Notes

- A meter socket is provided and is mounted on the door of all CT cabinets.

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.



Current Transformer Cabinets

City of Norway Area Units | UL listed

Underground Entry & Underground Exit

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
NORM-403-6	400	250	1Ø 3W	65kA	42	20	8
NORM-403-8	400	250	3Ø 3W	65kA	42	20	8
NORM-404-13	400	250	3Ø 4W	65kA	42	20	8
NORM-603-6UG	600	250	1Ø 3W	65kA	48	46	12
NORM-603-8UG	600	250	3Ø 3W	65kA	48	46	12
NORM-604-13UG	600	250	3Ø 4W	65kA	48	46	12
NORM-803-6UG	800	250	1Ø 3W	65kA	48	46	12
NORM-803-8UG	800	250	3Ø 3W	65kA	48	46	12
NORM-804-13UG	800	250	3Ø 4W	65kA	48	46	12
NORM-1203-8UG	1200	250	3Ø 3W	85kA	48	46	12
NORM-1204-13UG	1200	250	3Ø 4W	85kA	48	46	12
NORM-1603-8UG	1600	250	3Ø 3W	85kA	48	54	14
NORM-1604-13UG	1600	250	3Ø 4W	85kA	48	54	14
NORM-2004-13UG	2000	250	3Ø 4W	85kA	72	60	20
NORM-3004-13UG	3000	250	3Ø 4W	85kA	72	60	20

277/480V Units with provisions for mounting three potential transformers

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
NORM-464-13UGBX	400	600	3Ø4W	65kA	48	36	14
NORM-664-13UGBX	600	600	3Ø4W	65kA	48	36	14
NORM-864-13UGBX	800	600	3Ø4W	65kA	48	36	14
NORM-1264-13UGBX	1200	600	3Ø4W	85kA	48	54	14
NORM-1664-13UGBX	1600	600	3Ø4W	85kA	66	60	14
NORM-2064-13UGBX	2000	600	3Ø4W	85kA	66	60	14
NORM-3064-13UGBX	3000	600	3Ø4W	85kA	72	60	20

Notes

- A meter socket is provided and is mounted on the door of all CT cabinets.

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.

