

Current Transformer Cabinets

Kaukauna Area Units | UL listed



KAU-804-13UG

Overhead Entry

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
KAUM-404-13	400	600	3Ø4W	65kA	42	20	8
KAUM-603-6	600	600	1Ø3W	65kA	42	24	8
KAUM-604-13	600	600	3Ø4W	65kA	42	24	8
KAUM-803-6	800	600	1Ø3W	65kA	42	24	8
KAUM-804-13	800	600	3Ø4W	65kA	42	24	8

Underground Entry

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
KAUM-404-13	400	600	3Ø4W	65kA	42	20	8
KAUM-603-6UG	600	600	1Ø3W	65kA	48	46	12
KAUM-604-13UG	600	600	3Ø4W	65kA	48	46	12
KAUM-803-6UG	800	600	1Ø3W	65kA	48	46	12
KAUM-804-13UG	800	600	3Ø4W	65kA	48	46	12
KAUM-1204-13UG	1200	600	3Ø4W	85kA	48	46	12
KAUM-1604-13UG	1600	600	3Ø4W	85kA	48	54	14
KAUM-2004-13UG	2000	600	3Ø4W	85kA	60	60	14

Notes

- All Transockets include a single meter socket with pre-wired test switch, mounted on the door.

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.

