

# Current Transformer Cabinets

Menasha Electric Area Units | UL listed



**MENM-804**

## Underground Entry/Underground Exit

Catalog Number	Amps	Voltage	Phase	SCCR	Dimensions		
					H"	W"	D"
<b>MENM-403</b>	400	600	1Ø3W	65kA	42	20	8
<b>MENM-404</b>	400	600	3Ø4W	65kA	42	20	8
<b>MENM-603</b>	600	600	1Ø3W	65kA	42	24	8
<b>MENM-604</b>	600	600	3Ø4W	65kA	42	24	8
<b>MENM-803</b>	800	600	1Ø3W	65kA	42	24	8
<b>MENM-804</b>	800	600	3Ø4W	65kA	42	24	8
<b>MENM-1204UG</b>	1200	600	3Ø4W	85kA	48	46	12
<b>MENM-1604UG</b>	1600	600	3Ø4W	85kA	48	54	14
<b>MENM-2004UG</b>	2000	600	3Ø4W	85kA	72	60	20
<b>MENM-3004UG</b>	3000	600	3Ø4W	85kA	72	60	20

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.

