MILBANK ENERGYAT WORK

K4904

Number Of Feeders

Catalog Number	K4904
Marketing Product Description	Ct Mounting Rack 400 Ampere 3 Phase 50k Ampere Interrupting Capacity One 4-600kcmil Or Two 1-250kcmil EUSERC
UPC	784572255975
Length (IN)	6.204
Width (IN)	14.132
Height (IN)	23.469
Weight (LB)	26
Brand Name	Milbank
Туре	Current Transformer Mounting Rack
Application	Current Transformer Accessory
Standard	UL Listed
Voltage Rating	600 Volts Alternating Current
Phase	3 Phase
Frequency Rating	60 Hertz
Amperage Rating	400 Ampere
Short Circuit Rating	50,000 Ampere Interrupting Capacity
Connection	Lug
Insulation	Non-Metallic
	2

2



Material	

Plated Aluminum

Mounting

Surface Mount

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.