




**MILBANK**  
ENERGY AT WORK



## U3986-XL-100-LIS




Catalog Number	U3986-XL-100-LIS
Marketing Product Description	5 Terminal Ringless Large Hub Open Adapt To Small Hub Open Lever Bypass 1-100 Ampere Main Breaker Long Island Lighting Company
UPC	784572139275
Length (IN)	4.875
Width (IN)	13
Height (IN)	34
Brand Name	Milbank
Type	Ringless Meter Socket
Special Features	Long Island Lighting Company
Application	Meter Socket With Main
Standard	UL Listed;Type 3R
Voltage Rating	Up to 240 Volts Alternating Current
Amperage Rating	100 Continuous Ampere
Phase	1 Phase
Frequency Rating	60 Hertz
Size	4.875L x 13W x 34H
Number Of Cutouts	1
Cutout Size	One 100 Ampere Main Breaker
Cable Entry	Overhead or Underground

Terminal	Lay in
Insulation	Glass Polyester
Mounting	Surface Mount
Enclosure	G90 Galvanized Steel with Powder Coat Finish
Jaw Quantity	5 Terminal
Bypass Type	Lever Bypass
Number of Meter Positions	1 Position
Equipment Ground	3 Barrel Ground Lug
Hub Opening	Small Closing Plate
Line Side Wire Range	2 AWG - 350 kcmil
Load Side Wire Range	1 - 3 AWG
Number Of Receptacles	0

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.



FEATURE TABLE		
ITEM	QTY	DESCRIPTION
A	8	U/L MNTG.EMBOSS
B	1	1/4 SOLID K.O.
C	1	1/4, 1/2 CONC. K.O.
D	1	1 1/4, 1 1/2, 2, 2 1/2 CONC. K.O.
E	1	2, 2 1/2, 3 CONC. K.O.



Version:

1

**All dimensions are +/- 1/16".  
Drawing views are not to scale.**

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.