



MILBANK
ENERGY AT WORK

Q120



| | |
|-------------------------------|---|
| Catalog Number | Q120 |
| Marketing Product Description | Siemens 20 Ampere 1 Pole 120 Volts Plug-on 10k Ampere Interrupting Capacity |
| UPC | 784572369245 |
| Length (IN) | 2.555 |
| Width (IN) | 0.99 |
| Height (IN) | 3.188 |
| Weight (LB) | 0.5 |
| Brand Name | Milbank |
| Type | Current Interrupting Device |
| Special Features | Plug On |
| Application | Metering Accessory |
| Standard | UL Listed |
| Voltage Rating | 240 Volts Alternating Current |
| Current Rating | 20 Ampere |
| Frequency Rating | 60 Hertz |
| Number of Phases | 1 Phase |
| Frame | Small Frame |
| Trip Type | Thermal Magnetic |
| Interrupt Rating | 10,000 Ampere Interrupting Capacity |
| Number Of Poles | 1 |
| Actuator | Lever |

| | |
|-----------------------|-----------------------|
| Connection | Bus to Lug |
| Auxiliary Contacts | No Auxiliary Contacts |
| Material | Non Metallic |
| Operating Temperature | 40 Degrees Celsius |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.